

Anritsu envision : ensure

Vector Signal Generator

MG3710A

- 100 kHz to 2.7 GHz
- 100 kHz to 4.0 GHz
- 100 kHz to 6.0 GHz



MG3710A Vector Signal Generator

MG3710A
Vector Signal Generator

Reference Oscillator

Pre-installed

Aging Rate: $\pm 1 \times 10^{-7}$ /day

MG3710A-002/102

High Stability Reference Oscillator
Aging Rate: $\pm 1 \times 10^{-8}$ /day

MG3710A-001/101

Rubidium Reference Oscillator
Aging Rate: $\pm 1 \times 10^{-10}$ /month

Frequency Range for 1stRF

* Require one of following

MG3710A-032

1stRF 100 kHz to 2.7 GHz

MG3710A-034

1stRF 100 kHz to 4 GHz

MG3710A-036

1stRF 100 kHz to 6 GHz

MG3710A-041/141

High Power Extension for 1stRF

MG3710A-042/142

Low Power Extension for 1stRF

MG3710A-043/143

Reverse Power Protection for 1stRF

Frequency Range for 2ndRF

* Select one of following

MG3710A-062/162

2ndRF 100 kHz to 2.7 GHz

MG3710A-064/164

2ndRF 100 kHz to 4 GHz

MG3710A-066/166

2ndRF 100 kHz to 6 GHz

MG3710A-071/171

High Power Extension for 2ndRF

MG3710A-072/172

Low Power Extension for 2ndRF

MG3710A-073/173

Reverse Power Protection for 2ndRF

 Order at least one of these items.

Options with -0xx appended are standard options at shipment.

Options with -1xx can be retrofitted after shipment but no other option numbers can be retrofitted.

MG3710A-017/117
Universal Input/Output
(with J1539A)

MG3710A-021/121
BER Test Function
(with J1539A)

J1539A
AUX Conversion Adaptor

MG3710A-011/111
2ndary HDD

ARB Memory Upgrade

* Select one of following

Pre-installed for 1stRF
64 Msamples

MG3710A-045/145
ARB Memory Upgrade
256 Msample for 1stRF

MG3710A-046/146
ARB Memory Upgrade
1024 Msample for 1stRF

MG3710A-048/148
Combination of Baseband Signal for
1stRF

MG3710A-049/149
AWGN for 1stRF

MG3710A-050/150
Additional Analog Modulation Input
for 1stRF

MG3710A-018/118
Analog IQ Input/Output

ARB Memory Upgrade

* Select one of following

Pre-installed for 2ndRF
64 Msamples

MG3710A-075/175
ARB Memory Upgrade
256 Msample for 2ndRF

MG3710A-076/176
ARB Memory Upgrade
1024 Msample for 2ndRF

MG3710A-078/178
Combination of Baseband Signal for
2ndRF

MG3710A-079/179
AWGN for 2ndRF

MG3710A-080/180
Additional Analog Modulation Input
for 2ndRF

This document explains how to order the new MG3710A and MG3710A retrofit options and software. Follow the steps below to select your MG3710A configuration. Functions marked standard are built-in at factory shipment. Options and software can be added as necessary. Two RF outputs (1stRF and 2ndRF) can be installed in the MG3710A. The options for each RF output are color coded as follows:

| | | |
|-------------------------------------|---------------------------|---------------------------|
| Options for both 1stRF and 2ndRF | Options only for 1stRF | Options only for 2ndRF |
|-------------------------------------|---------------------------|---------------------------|

To add options to the MG3710A order as follows:

Example

| | |
|--------|-------------|
| Model | MG3710A |
| Option | MG3710A-032 |
| Option | MG3710A-048 |

Step. 1 Choose frequency range for 1stRF.

(Required option: The frequency range cannot be upgraded.)

| Name | Option No. | Additional Information |
|--------------------------|-------------|---|
| 1stRF 100 kHz to 2.7 GHz | MG3710A-032 | 1stRF output of vector signal generator. |
| 1stRF 100 kHz to 4 GHz | MG3710A-034 | Select the model with the required frequency range. |
| 1stRF 100 kHz to 6 GHz | MG3710A-036 | The 1stRF frequency cannot be changed retroactively after ordering. |

Step. 2 Choose frequency range for 2ndRF.

(This extra option cannot be retrofitted.)

| Name | Option No. | Additional Information |
|--------------------------|-------------|---|
| 2ndRF 100 kHz to 2.7 GHz | MG3710A-062 | 2ndRF output of vector signal generator. |
| 2ndRF 100 kHz to 4 GHz | MG3710A-064 | Select one model with the required frequency range. |
| 2ndRF 100 kHz to 6 GHz | MG3710A-066 | The 2ndRF frequency cannot be changed retroactively after ordering. |

Step. 3 Choose frequency reference.

Choose one reference oscillator. The selected reference oscillator performance is enabled and other reference oscillators are disabled.

| Name | Option No. | Additional Information |
|-------------------------------------|-------------|---|
| Standard Reference Oscillator | Standard | Aging Rate: $\pm 1 \times 10^{-6}$ /year, $\pm 1 \times 10^{-7}$ /day |
| Rubidium Reference Oscillator | MG3710A-001 | Aging Rate: $\pm 1 \times 10^{-10}$ /month |
| High Stability Reference Oscillator | MG3710A-002 | Aging Rate: $\pm 1 \times 10^{-7}$ /year, $\pm 1 \times 10^{-8}$ /day |

Step. 4 Select the signal output level setting range expansion and the reverse input power protection.

| Name | Option No. | Additional Information |
|------------------------------------|-------------|--|
| High Power Extension for 1stRF | MG3710A-041 | Extends signal output setting range upper limit (Standard +17 dBm) Opt. 041/141 installed and Opt. 043/143 not installed, CW Level setting range: Hi limit +30 dBm Opt. 041/141 installed and Opt. 043/143 installed, CW Level setting range: Hi limit +25 dBm |
| Low Power Extension for 1stRF | MG3710A-042 | Extends signal output setting range lower limit (Standard -110 dBm) Level setting range: Lo limit -144 dBm |
| Reverse Power Protection for 1stRF | MG3710A-043 | Protects signal output connector against reverse input power (Standard 2 W nominal) Max. reverse input: 20 W nominal (1 MHz < frequency ≤ 2 GHz) 10 W nominal (2 GHz < frequency ≤ 6 GHz) |
| High Power Extension for 2ndRF | MG3710A-071 | Extends signal output setting range upper limit (Standard +17 dBm) Opt. 071/171 installed and Opt. 073/173 not installed, CW Level setting range: Hi limit +30 dBm Opt. 071/171 installed and Opt. 073/173 installed, CW Level setting range: Hi limit +25 dBm |
| Low Power Extension for 2ndRF | MG3710A-072 | Extends signal output setting range lower limit (Standard -110 dBm) Level setting range: Lo limit -144 dBm |
| Reverse Power Protection for 2ndRF | MG3710A-073 | Protects signal output connector against reverse input power (Standard 2 W nominal) Max. reverse input: 20 W nominal (1 MHz < frequency ≤ 2 GHz) 10 W nominal (2 GHz < frequency ≤ 6 GHz) |

● Setting Range of the Signal output level

| Options | Setting Range [dBm] | |
|---------------------------------|---------------------|-------------|
| | Without RPP* | With RPP* |
| Standard | -110 to +17 | -110 to +17 |
| With High Power Extension | -110 to +30 | -110 to +25 |
| With Low Power Extension | -144 to +17 | -144 to +17 |
| With High & Low Power Extension | -144 to +30 | -144 to +25 |

*RPP: Reverse Power Protection

● Accuracy guaranteed upper limit level of the signal output level

Without Reverse Power Protection

| Frequency Range | Without High Power Extension | With High Power Extension |
|----------------------|------------------------------|---------------------------|
| 100 kHz ≤ f < 10 MHz | +5 dBm | +5 dBm |
| 10 MHz ≤ f < 50 MHz | +10 dBm | +10 dBm |
| 50 MHz ≤ f < 400 MHz | +13 dBm | +20 dBm |
| 400 MHz ≤ f ≤ 3 GHz | | +23 dBm |
| 3 GHz < f ≤ 4 GHz | | +20 dBm |
| 4 GHz < f ≤ 5 GHz | | +13 dBm |
| 5 GHz < f ≤ 6 GHz | +11 dBm | +11 dBm |

With Reverse Power Protection

| Frequency Range | Without High Power Extension | With High Power Extension |
|----------------------|------------------------------|---------------------------|
| 100 kHz ≤ f < 10 MHz | +2 dBm | +2 dBm |
| 10 MHz ≤ f < 50 MHz | +7 dBm | +7 dBm |
| 50 MHz ≤ f < 400 MHz | +10 dBm | +17 dBm |
| 400 MHz ≤ f ≤ 3 GHz | | +20 dBm |
| 3 GHz < f ≤ 4 GHz | | +17 dBm |
| 4 GHz < f ≤ 5 GHz | | +10 dBm |
| 5 GHz < f ≤ 6 GHz | +8 dBm | +8 dBm |

Step. 5 Select the baseband vector signal generator ARB memory size option.

The selected memory is enabled and others are disabled.

| Name | Option No. | Additional Information |
|---|-------------|---|
| ARB Memory 64 Msample for 1stRF | Standard | Standard baseband generator for 160 MHz sampling rate and 64 Msamples ARB memory size (256 MB) |
| ARB Memory Upgrade 256 Msample for 1stRF | MG3710A-045 | Upgrades ARB size to 256 Msamples (1 GB) With Opt. 048/148 not installed, installs 1 × 256 Msamples With Opt. 048/148 installed, installs 2 × 256 Msamples |
| ARB Memory Upgrade 1024 Msample for 1stRF | MG3710A-046 | Upgrades ARB size to 1024 Msamples (4 GB) With Opt. 048/148 not installed, installs 1 × 1024 Msamples With Opt. 048/148 installed, installs 2 × 1024 Msamples |
| ARB Memory 64 Msample for 2ndRF | Standard | Standard baseband generator for 160 MHz sampling rate and 64 Msamples waveform memory size (256 MB) |
| ARB Memory Upgrade 256 Msample for 2ndRF | MG3710A-075 | Upgrades ARB size to 256 Msamples (1 GB) With Opt. 078/178 not installed, installs 1 × 256 Msamples With Opt. 078/178 installed, installs 2 × 256 Msamples |
| ARB Memory Upgrade 1024 Msample for 2ndRF | MG3710A-076 | Upgrades ARB size to 1024 Msamples (4 GB) With Opt. 078/178 not installed, installs 1 × 1024 Msamples With Opt. 078/178 installed, installs 2 × 1024 Msamples |

Note: Since each waveform pattern size is different, if the memory is not upgraded, sometimes the waveform pattern cannot be used.
For details, refer to the Waveform Pattern Catalog and the IQproducer catalog.

Step. 6 Select the baseband signal combine and AWGN function options.

| Name | Option No. | Additional Information |
|--|-------------|---|
| Combination of Baseband Signal for 1stRF | MG3710A-048 | Two internal ARB memories. Selects two waveform patterns per one RF output for setting mutual frequency offset, level offset, delay time, etc., to output 2 signals from 1 RF connector |
| AWGN for 1stRF | MG3710A-049 | Internal AWGN addition function. Adjusts AWGN bandwidth range setting as follows for selected waveform pattern: Band limit: waveform pattern sampling rate × 0.2 to waveform pattern sampling rate × 0.8 CN: ≤40 dB |
| Combination of Baseband Signal for 2ndRF | MG3710A-078 | Two internal ARB memories. Selects two waveform patterns per one RF output for setting mutual frequency offset, level offset, delay time, etc., to output 2 signals from 1 RF connector |
| AWGN for 2ndRF | MG3710A-079 | Internal AWGN addition function. Adjusts AWGN bandwidth range setting as follows for selected waveform pattern: Band limit: waveform pattern sampling rate × 0.2 to waveform pattern sampling rate × 0.8 CN: ≤40 dB |

Step. 7 Choose the analog input/output options.

| Name | Option No. | Additional Information |
|------------------------|-------------|---|
| Analog IQ Input/Output | MG3710A-018 | Installs analog I/Q input and output connectors on rear panel of main frame but only supports SG1 side (1stRF side) |

Step. 8 Choose the external input/output options.

| Name | Option No. | Additional Information |
|--|-------------|---|
| Universal Input/Output | MG3710A-017 | Installs following signal I/O connectors on rear panel of main frame Baseband Reference Clock Input/Output Sweep Output (only supports 1stRF) Local Signal Input/Output *: Also provides J1539A AUX Conversion Adapter for Opt. 017/117 to use rear panel AUX connector |
| AUX Conversion Adapter | J1539A | Adapter for converting rear panel AUX connector to BNC connector |
| Additional Analog Modulation Input for 1stRF | MG3710A-050 | Adds additional analog modulation inputs function for 1stRF. Extends to two internal modulation sources (AM/FM/ΦM), and one external modulation source supporting simultaneous two-signal modulation. Installs external signal input connector on rear panel of main unit. |
| Additional Analog Modulation Input for 2ndRF | MG3710A-080 | Adds additional analog modulation inputs function for 2ndRF. Extends to two internal modulation sources (AM/FM/ΦM), and one external modulation source supporting simultaneous two-signal modulation. Installs external signal input connector on rear panel of main unit. |

Step. 9 Choose the BER test function.

| Name | Option No. | Additional Information |
|-------------------|-------------|--|
| BER Test Function | MG3710A-021 | Installs BER measurement function Input signals: Data, Clock, Enable Bit rate: 100 bps to 40 Mbps *: Also provides J1539A AUX Conversion Adapter for Opt. 021/121 to use rear panel AUX connector |

Step. 10 Choose HDD option.

| Name | Option No. | Additional Information |
|------------|-------------|--------------------------------|
| 2ndary HDD | MG3710A-011 | User installable/removable HDD |

Step. 11 Choose warranty options.

| Name | Option No. | Additional Information |
|-----------------------------------|---------------|------------------------|
| 1 Year Warranty Service | Standard | Excludes consumables |
| 2 Years Extended Warranty Service | MG3710A-ES210 | |
| 3 Years Extended Warranty Service | MG3710A-ES310 | |
| 5 Years Extended Warranty Service | MG3710A-ES510 | |

Step. 12 Choose waveform pattern software.

The waveform pattern software function sets the selected waveform using previously set parameters. The waveform patterns are installed in the MG3710A and the signal is output by selecting them.

When outputting a waveform pattern from the MG3710A, no signal is output unless a license for that system is installed in the main frame.

Note: Since the size of each waveform pattern is different, sometimes waveforms cannot be output if the memory upgrade option has not been installed.

For details refer to the waveform pattern catalog.

| Name | Option No. | Additional Information |
|-----------------------------|------------|---|
| Standard Waveform Patterns* | Standard* | LTE FDD (E-TM1.1 to E-TM3.3), LTE TDD (E-TM1.1 to E-TM3.3), W-CDMA/HSDPA, GSM/EDGE, CDMA2000 1X/1xEV-DO, Bluetooth®, GPS, PDC, PHS, Broadcast (ISDB-T/BS/CS/CATV), WLAN (IEEE802.11a/11b/11g) |
| DFS Radar Pattern | MX370073A | [to be discontinued in May 2019] Sets pulse signals for testing 5-GHz band WLAN DFS functions. The MX370073A supports the waveform patterns for the FCC and Japan MIC (TELEC) test specifications. Pulse signals are output simply by selecting the pattern. |
| DFS Radar Pattern | MX370073B | Sets pulse signals for testing 5-GHz band WLAN DFS functions. The MX370073B supports the waveform patterns for the FCC and Japan MIC (TELEC) test specifications. Pulse signals are output simply by selecting the pattern. |
| DFS (ETSI) Waveform Pattern | MX370075A | Sets pulse signals for testing 5-GHz band WLAN DFS functions. The MX370075A supports the waveform patterns for the ETSI specifications. Pulse signals are output simply by selecting the pattern. |
| ISDB-Tmm Waveform Pattern | MX370084A | Archive of ARIB STD-B46 waveform patterns. Supports MER and spectrum evaluation of Tx characteristics tests and sensitivity/ simple BER tests at Rx characteristics tests. |

*: The following option is installed as standard when ordering the MG3710A. It does not require a separate order.

Option No.: MX371099A

Name: MG3710A Standard Waveform Pattern

Step. 13 Choose IQproducer software license.

IQproducer is PC application software for generating waveform patterns. The parameters are set using IQproducer and the waveform pattern is created to output the signal by selection at the MG3710A. This one software application includes all the following systems.

Since it runs on any PC, the supported functions and parameter range can be verified before purchase.

When outputting a waveform pattern from the MG3710A, no signal is output unless a license for that system is installed in the main frame.

Note: Since the size of each waveform pattern is different, sometimes waveforms cannot be output if the memory upgrade option has not been installed.

For details refer to the waveform pattern catalog.

| Name | Option No. | Additional Information |
|-------------------------------|---------------|--|
| HSDPA/HSUPA IQproducer | MX370101A | Sets parameters according to 3GPP HSDPA/HSUPA (Uplink and Downlink) specifications, and generates HSDPA/HSUPA waveform patterns including Fixed Reference Channel (3GPP TS 25.101 Annex A.7). |
| TDMA IQproducer | MX370102A | Sets required parameters for TDMA waveform patterns and generates various waveform patterns. Setting parameters include Modulation, Frame, Slot, Data, Filter, etc. Supports wide application range including public wireless. |
| CDMA2000 1xEV-DO IQproducer | MX370103A | Sets parameters according to CDMA2000 1xEV-DO Forward/Reverse specifications and generates 1xEV-DO waveform patterns. |
| Multi-carrier IQproducer | MX370104A | Generates multi-carrier waveform patterns combination files using MG3710A Baseband Signal Combine function (requires Opt. 048/078). |
| Mobile WiMAX IQproducer | MX370105A | Sets parameters according to IEEE 802.16e-2005, IEEE P802.16Rev2/D3 WirelessMAN-OFDMA MAC, PHY specifications and generates waveform patterns. Supports WirelessMAN-OFDMA specification used by 802.16e mobile standard. |
| DVB-T/H IQproducer | MX370106A | Sets parameters according to ETSI EN 300 744 V1.5.1 (2004-11) physical layer standard and generates DVB-T/H waveform patterns. Generated waveform patterns can be used for device TRx characteristics evaluation tests (Error Correction BER, graphics). |
| Fading IQproducer | MX370107A | Performs IQ channel fading processing, correlation matrix calculation, AWGN combination. Input data file created by selecting waveform pattern file created with other IQproducer software, and IQ data (ASCII) created with other general-purpose simulation tools. |
| LTE IQproducer | MX370108A | Generates wanted waveform patterns with parameters modified according to 3GPP TS 36.211, TS 36.212, TS 36.213 LTE FDD specifications. |
| LTE-Advanced FDD Option | MX370108A-001 | Installing in the MX370108A supports simple generation of carrier aggregation signals added by 3GPP Rel. 10. Additionally, clustered SC-FDMA signals can be generated at Uplink. *: Requires MX370108A |
| LTE TDD IQproducer | MX370110A | Generates wanted waveform patterns with parameters modified according to 3GPP TS 36.211, TS 36.212, TS 36.213 LTE TDD specifications. |
| LTE-Advanced TDD Option | MX370110A-001 | Installing in the MX370110A supports simple generation of carrier aggregation signals added by 3GPP Rel. 10. Additionally, clustered SC-FDMA signals can be generated at Uplink. *: Requires MX370110A |
| WLAN IQproducer | MX370111A | Generates waveform patterns for IEEE Std 802.11-2007 and IEEE Std 802.11n-2009 IEEE 802.11a/b/g/j/n/p specifications. |
| 802.11ac (160 MHz) Option | MX370111A-002 | Installing in the MX370111A supports waveform patterns generation compliant with LTE-Advanced FDD specifications. *: Requires MX370111A. Only for MG3710A |
| TD-SCDMA IQproducer | MX370112A | Generates wanted waveform patterns with parameters modified according to TD-SCDMA specifications standardized by TRx characteristics evaluation tests (excluding performance tests) for 3GPP TS 25.221, TS 25.222, TS 25.223, TS 25.105, TS 25.142 |
| 5G NR TDD sub-6GHz IQproducer | MX370113A | Generates 3GPP TS 38.211, TS 38.212 and TS 38.213-compliant 5G NR FR1 waveform patterns used by the Tx test for 5G NR base stations (BS) as well as Fixed Reference Channel (FRC) waveform patterns used by the Rx test. |

Retrofit to Current MG3710A

Hardware Option Retrofits

The following hardware options can be retrofitted. Order the Z1572A Installation Kit as well. The MG3710A must be returned to the Anritsu plant for hardware retrofitting.

| Name | Option No. | Additional Information | Reference Steps |
|--|-------------|---|-----------------|
| Options for both 1stRF and 2ndRF | | | |
| Rubidium Reference Oscillator | MG3710A-101 | | 3 |
| High Stability Reference Oscillator | MG3710A-102 | | 3 |
| 2ndary HDD | MG3710A-111 | | 10 |
| Universal Input/Output | MG3710A-117 | | 8 |
| BER Test Function | MG3710A-121 | | 9 |
| CPU/Windows7 Upgrade Retrofit | MG3710A-181 | This option is for MG3710A units ordered until May 2018. It upgrades the currently installed CPU to a faster CPU and the OS to Windows 7 (WEST). Due to OS license restrictions, this option is not applicable to MG3710A units in which Opt. 313 Removable HDD (sales discontinued) is installed. | — |
| 1stRF Options | | | |
| Analog IQ Input/Output | MG3710A-118 | | 7 |
| High Power Extension for 1stRF | MG3710A-141 | | 4 |
| Low Power Extension for 1stRF | MG3710A-142 | | 4 |
| Reverse Power Protection for 1stRF | MG3710A-143 | | 4 |
| ARB Memory Upgrade 256 Msample for 1stRF | MG3710A-145 | Not simultaneously with Opt. 046/146 | 5 |
| ARB Memory Upgrade 1024 Msample for 1stRF | MG3710A-146 | Not simultaneously with Opt. 045/145 | 5 |
| Combination of Baseband Signal for 1stRF | MG3710A-148 | | 6 |
| AWGN for 1stRF | MG3710A-149 | | 6 |
| Additional Analog Modulation Input for 1stRF | MG3710A-150 | | 8 |
| 2ndRF Options | | | |
| 2ndRF 100 kHz to 2.7 GHz | MG3710A-162 | Cannot be installed if 2ndRF option not installed | 2 |
| 2ndRF 100 kHz to 4 GHz | MG3710A-164 | Cannot be installed if 2ndRF option not installed | 2 |
| 2ndRF 100 kHz to 6 GHz | MG3710A-166 | Cannot be installed if 2ndRF option not installed | 2 |
| High Power Extension for 2ndRF | MG3710A-171 | | 4 |
| Low Power Extension for 2ndRF | MG3710A-172 | | 4 |
| Reverse Power Protection for 2ndRF | MG3710A-173 | | 4 |
| ARB Memory Upgrade 256 Msample for 2ndRF | MG3710A-175 | Not simultaneously with Opt. 076/176 | 5 |
| ARB Memory Upgrade 1024 Msample for 2ndRF | MG3710A-176 | Not simultaneously with Opt. 075/175 | 5 |
| Combination of Baseband Signal for 2ndRF | MG3710A-178 | | 6 |
| AWGN for 2ndRF | MG3710A-179 | | 6 |
| Additional Analog Modulation Input for 2ndRF | MG3710A-080 | | 8 |
| Application parts | | | |
| Installation Kit | Z1572A | Required when retrofitting hardware options or installing IQproducer (MX3701xxA) | — |

Software Option Retrofits

The following software options can be retrofitted. Order the Z1572A Installation Kit as well.
The MG3710A does not require return to the Anritsu plant for software retrofitting.

| Name | Option No. | Additional Information | Reference Steps |
|-------------------------------|---------------|--|-----------------|
| Waveform Patterns | | | |
| DFS Radar Pattern | MX370073A | to be discontinued in May 2019 | 12 |
| DFS Radar Pattern | MX370073B | | 12 |
| DFS (ETSI) Waveform Pattern | MX370075A | | 12 |
| ISDB-Tmm Waveform Pattern | MX370084A | | 12 |
| IQproducer | | | |
| HSDPA/HSUPA IQproducer | MX370101A | | 13 |
| TDMA IQproducer | MX370102A | | 13 |
| CDMA2000 1xEV-DO IQproducer | MX370103A | | 13 |
| Multi-carrier IQproducer | MX370104A | | 13 |
| Mobile WiMAX IQproducer | MX370105A | | 13 |
| DVB-T/H IQproducer | MX370106A | | 13 |
| Fading IQproducer | MX370107A | | 13 |
| LTE IQproducer | MX370108A | | 13 |
| LTE-Advanced FDD Option | MX370108A-001 | *: Requires MX370108A | 13 |
| LTE TDD IQproducer | MX370110A | | 13 |
| LTE-Advanced TDD Option | MX370110A-001 | *: Requires MX370110A | 13 |
| WLAN IQproducer | MX370111A | | 13 |
| 802.11ac (160 MHz) Option | MX370111A-002 | *: Requires MX370111A. Only for MG3710A | 13 |
| TD-SCDMA IQproducer | MX370112A | | 13 |
| 5G NR TDD sub-6GHz IQproducer | MX370113A | | 13 |
| Application parts | | | |
| Installation Kit | Z1572A | Required when retrofitting hardware options or installing IQproducer (MX3701xxA) | — |

Options Configuration Guide

The following table shows the recommended option combinations.

| Type | Opt. No | Retrofit | Name | 032 | 034 | 036 | 018 | 041 | 042 | 043 | 045 | 046 | 048 |
|--------|-------------|----------|--|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| 1stRF | MG3710A-032 | | 1stRF 100 kHz to 2.7 GHz | | *1 | *1 | | | | | | | |
| 1stRF | MG3710A-034 | | 1stRF 100 kHz to 4 GHz | *1 | | *1 | | | | | | | |
| 1stRF | MG3710A-036 | | 1stRF 100 kHz to 6 GHz | *1 | *1 | | | | | | | | |
| 1stRF | MG3710A-018 | 118 | Analog IQ Input/Output | | | | | | | | | | |
| 1stRF | MG3710A-041 | 141 | High Power Extension for 1stRF | | | | | | | | | | |
| 1stRF | MG3710A-042 | 142 | Low Power Extension for 1stRF | | | | | | | | | | |
| 1stRF | MG3710A-043 | 143 | Reverse Power Protection for 1stRF | | | | | | | | | | |
| 1stRF | MG3710A-045 | 145 | ARB Memory Upgrade 256 Msample for 1stRF | | | | | | | | | *3 | |
| 1stRF | MG3710A-046 | 146 | ARB Memory Upgrade 1024 Msample for 1stRF | | | | | | | | *3 | | |
| 1stRF | MG3710A-048 | 148 | Combination of Baseband Signal for 1stRF | | | | | | | | | | |
| 1stRF | MG3710A-049 | 149 | AWGN for 1stRF | | | | | | | | | | |
| 1stRF | MG3710A-050 | 150 | Additional Analog Modulation Input for 1stRF | | | | | | | | | | |
| 2ndRF | MG3710A-062 | 162 | 2ndRF 100 kHz to 2.7 GHz | | | | | | | | | | |
| 2ndRF | MG3710A-064 | 164 | 2ndRF 100 kHz to 4 GHz | | | | | | | | | | |
| 2ndRF | MG3710A-066 | 166 | 2ndRF 100 kHz to 6 GHz | | | | | | | | | | |
| 2ndRF | MG3710A-071 | 171 | High Power Extension for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-072 | 172 | Low Power Extension for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-073 | 173 | Reverse Power Protection for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-075 | 175 | ARB Memory Upgrade 256 Msample for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-076 | 176 | ARB Memory Upgrade 1024 Msample for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-078 | 178 | Combination of Baseband Signal for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-079 | 179 | AWGN for 2ndRF | | | | | | | | | | |
| 2ndRF | MG3710A-080 | 180 | Additional Analog Modulation Input for 2ndRF | | | | | | | | | | |
| Common | MG3710A-001 | 101 | Rubidium Reference Oscillator | | | | | | | | | | |
| Common | MG3710A-002 | 102 | High Stability Reference Oscillator | | | | | | | | | | |
| Common | MG3710A-011 | 111 | 2ndary HDD | | | | | | | | | | |
| Common | MG3710A-017 | 117 | Universal Input/Output | | | | | | | | | | |
| Common | MG3710A-021 | 121 | BER Test Function | | | | | | | | | | |

*1: Only one of 2.7 GHz, 4 GHz, and 6 GHz options. Install any one 1stRF option. Retrofitting one of these options disables previously installed option.

*2: Only one of 2.7 GHz, 4 GHz, and 6 GHz options. Retrofitting one of these options disables previously installed option. Install any one 2ndRF option.
Can be retrofitted only when 2ndRF not installed.

*3: Select any one. Selected memory size enabled and all others disabled.

Maximum Waveform Pattern Size and Required Options for Simultaneous Use

• 1stRF (Opt. 032/034/036)

| Combination of Baseband Signal (Opt. 048) | ARB Memory Upgrade 256 Msample (Opt. 045) ARB Memory Upgrade 1024 Msample (Opt. 046) | | |
|---|---|---|-------------------------|
| | W/O | With Opt. 045 | With Opt. 046 |
| W/O | 64 Msamples x 1 pc | 256 Msamples x 1 pc | 1024 Msamples x 1 pc*1 |
| With Opt. 048*2 | 64 Msamples x 2 pcs 128 Msamples x 1 pc | 256 Msamples x 2 pcs 512 Msamples x 1 pc | 1024 Msamples x 2 pcs*1 |

• 2ndRF (Opt. 062/064/066)

| Combination of Baseband Signal (Opt. 078) | ARB Memory Upgrade 256 Msample (Opt. 075) ARB Memory Upgrade 1024 Msample (Opt. 076) | | |
|---|---|---|-------------------------|
| | W/O | With Opt. 075 | With Opt. 076 |
| W/O | 64 Msamples x 1 pc | 256 Msamples x 1 pc | 1024 Msamples x 1 pc*1 |
| With Opt. 078*2 | 64 Msamples x 2 pcs 128 Msamples x 1 pc | 256 Msamples x 2 pcs 512 Msamples x 1 pc | 1024 Msamples x 2 pcs*1 |

*1: The maximum size per waveform pattern supported by the MG3710A varies with the IQproducer version.

For details refer to the MG3710A catalog.

*2: The Baseband Signal Combine option supports two ARB memories and can either set two different waveform patterns or combine them as one memory to support one large waveform pattern.

Ordering Information

Please specify the model/order number, name and quantity when ordering.
The names listed in the chart below are Order Names. The actual name of the item may differ from the Order Name.

| Model/Order No. | Name | Remarks |
|---|---|--|
| MG3710A | - Main frame - Vector Signal Generator | |
| P0031A | - Standard accessories - Power Cord: USB Memory Install CD-ROM | 1 pc USB2.0 Flash Driver, ≥256 MB Operation manual (PDF) and application software (IQproducer) |
| MG3710A-001 MG3710A-002 MG3710A-011 MG3710A-017 | - Options - (Common Parts) Rubidium Reference Oscillator High Stability Reference Oscillator 2ndary HDD Universal Input/Output | Select when ordering main frame, aging rate: $\pm 1 \times 10^{-10}$ /month Select when ordering main frame, aging rate: $\pm 1 \times 10^{-7}$ /year Select when ordering main frame, spare HDD for saving user data without Windows OS Select when ordering main frame, Adds BNC connectors for following signals to rear panel of main frame, includes J1539A AUX Conversion Adapter (Baseband Reference Clock Input/Output, Sweep Output, Local Signal Input/Output) Select when ordering main frame, Built-in BER measurement, Bit Rate: 100 bps to 40 Mbps J1539A AUX Conversion Adapter required for Data/Clock/Enable signal input |
| MG3710A-021 | BER Test Function | Retrofitted to shipped MG3710A |
| MG3710A-101 MG3710A-102 MG3710A-111 MG3710A-117 MG3710A-121 MG3710A-181 | Rubidium Reference Oscillator Retrofit High Stability Reference Oscillator Retrofit 2ndary HDD Retrofit Universal Input/Output Retrofit BER Test Function Retrofit CPU/Windows7 Upgrade Retrofit | Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A This option is for MG3710A units ordered until May 2018. It upgrades the currently installed CPU to a faster CPU and the OS to Windows 7 (WES7). Due to OS license restrictions, this option is not applicable to MG3710A units in which Opt. 313 Removable HDD (sales discontinued) is installed. |
| MG3710A-032 | (For 1stRF) 1stRF 100 kHz to 2.7 GHz | Select when ordering main frame, select 1stRF frequency range, frequency cannot be changed after installation |
| MG3710A-034 | 1stRF 100 kHz to 4 GHz | Select when ordering main frame, select 1stRF frequency range, frequency cannot be changed after installation |
| MG3710A-036 | 1stRF 100 kHz to 6 GHz | Select when ordering main frame, select 1stRF frequency range, frequency cannot be changed after installation |
| MG3710A-041 MG3710A-042 MG3710A-043 | High Power Extension for 1stRF Low Power Extension for 1stRF Reverse Power Protection for 1stRF | Select when ordering main frame, increases upper limit of output signal power setting range Select when ordering main frame, increases lower limit of output signal power setting range Select when ordering main frame, prevents damage caused by reverse input to output connector |
| MG3710A-045 MG3710A-046 MG3710A-048 MG3710A-049 MG3710A-050 | ARB Memory Upgrade 256 Msample for 1stRF ARB Memory Upgrade 1024 Msample for 1stRF Combination of Baseband Signal for 1stRF AWGN for 1stRF Additional Analog Modulation Input for 1stRF | Select when ordering main frame, expands ARB memory capacity Select when ordering main frame, expands ARB memory capacity Select when ordering main frame, adds baseband combine function Select when ordering main frame, adds AWGN combine function Select when ordering main frame, Adds BNC connector for inputting external signals to rear panel of mainframe. |
| MG3710A-018 MG3710A-141 MG3710A-142 MG3710A-143 MG3710A-145 MG3710A-146 MG3710A-148 MG3710A-149 MG3710A-150 MG3710A-118 | Analog IQ Input/Output High Power Extension for 1stRF Retrofit Low Power Extension for 1stRF Retrofit Reverse Power Protection for 1stRF Retrofit ARB Memory Upgrade 256 Msample for 1stRF Retrofit ARB Memory Upgrade 1024 Msample for 1stRF Retrofit Combination of Baseband Signal for 1stRF Retrofit AWGN for 1stRF Retrofit Additional Analog Modulation Input for 1stRF Retrofit Analog IQ Input/Output Retrofit | Select when ordering main frame, installs IQ input/output BNC connector in main frame Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A |
| MG3710A-062 | (For 2ndRF) 2ndRF 100 kHz to 2.7 GHz | Select when ordering main frame, select 2ndRF frequency range, frequency cannot be changed after installation |
| MG3710A-064 | 2ndRF 100 kHz to 4 GHz | Select when ordering main frame, select 2ndRF frequency range, frequency cannot be changed after installation |
| MG3710A-066 | 2ndRF 100 kHz to 6 GHz | Select when ordering main frame, select 2ndRF frequency range, frequency cannot be changed after installation |
| MG3710A-071 MG3710A-072 MG3710A-073 MG3710A-075 MG3710A-076 MG3710A-078 MG3710A-079 MG3710A-080 | High Power Extension for 2ndRF Low Power Extension for 2ndRF Reverse Power Protection for 2ndRF ARB Memory Upgrade 256 Msample for 2ndRF ARB Memory Upgrade 1024 Msample for 2ndRF Combination of Baseband Signal for 2ndRF AWGN for 2ndRF Additional Analog Modulation Input for 2ndRF | Select when ordering main frame, increases upper limit of output signal power setting range Select when ordering main frame, increases lower limit of output signal power setting range Select when ordering main frame, prevents damage caused by reverse input to output connector Select when ordering main frame, expands ARB memory capacity Select when ordering main frame, expands ARB memory capacity Select when ordering main frame, adds baseband combine function Select when ordering main frame, adds AWGN combine function Select when ordering main frame, Adds BNC connector for inputting external signals to rear panel of mainframe. |
| MG3710A-162 MG3710A-164 MG3710A-166 MG3710A-171 MG3710A-172 MG3710A-173 MG3710A-175 MG3710A-176 MG3710A-178 MG3710A-179 MG3710A-180 | 2ndRF 100 kHz to 2.7 GHz Retrofit 2ndRF 100 kHz to 4 GHz Retrofit 2ndRF 100 kHz to 6 GHz Retrofit High Power Extension for 2ndRF Retrofit Low Power Extension for 2ndRF Retrofit Reverse Power Protection for 2ndRF Retrofit ARB Memory Upgrade 256 Msample for 2ndRF Retrofit ARB Memory Upgrade 1024 Msample for 2ndRF Retrofit Combination of Baseband Signal for 2ndRF Retrofit AWGN for 2ndRF Retrofit Additional Analog Modulation Input for 2ndRF Retrofit | Retrofitted to shipped MG3710A when 2ndRF not installed Retrofitted to shipped MG3710A when 2ndRF not installed Retrofitted to shipped MG3710A when 2ndRF not installed Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A Retrofitted to shipped MG3710A |
| MG3710A-ES210 MG3710A-ES310 MG3710A-ES510 | - Maintenance service - 2 Years Extended Warranty Service 3 Years Extended Warranty Service 5 Years Extended Warranty Service | |
| MX370073A MX370073B MX370075A MX370084A | - Softwares - (Waveform pattern) DFS Radar Pattern DFS Radar Pattern DFS (ETSI) Waveform Pattern ISDB-Tmm Waveform Pattern | (License for waveform patterns) [to be discontinued in May 2019] WLAN 5.3/5.6 GHz band DFS tests (for FCC and Japan MIC (TELECOM)) waveform pattern, license for main frame, manual (PDF) WLAN 5.3/5.6 GHz band DFS tests (for FCC and Japan MIC (TELECOM)) waveform pattern, license for main frame, manual (PDF) WLAN 5.3/5.6 GHz DFS test (ETSI) waveform pattern, license for main frame, manual (PDF) ISDB-Tmm Waveform Patterns, license for main frame, manual (PDF) |

| Model/Order No. | Name | Remarks |
|---|--|---|
| MX370101A MX370102A MX370103A MX370104A MX370105A MX370106A MX370107A MX370108A MX370108A-001 MX370110A MX370110A-001 MX370111A MX370111A-002 | - Softwares - (IQproducer) HSDPA/HSUPA IQproducer TDMA IQproducer CDMA2000 1xEV-DO IQproducer Multi-carrier IQproducer Mobile WiMAX IQproducer DVB-T/H IQproducer Fading IQproducer LTE IQproducer LTE-Advanced FDD Option LTE TDD IQproducer LTE-Advanced TDD Option WLAN IQproducer 802.11ac (160 MHz) Option | (License for IQproducer) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF). Requires MX370108A. IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF). Requires MX370110A. IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF). Only for MG3710A. Requires MX370111A IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) |
| MX370112A MX370113A | TD-SCDMA IQproducer 5G NR TDD sub-6GHz IQproducer | IQproducer software, license for main frame, manual (PDF) IQproducer software, license for main frame, manual (PDF) |
| W3580AE W2496AE W3581AE W3596AE W3986AE W3597AE W3508AE W2915AE W2916AE W2505AE W2917AE W2918AE W2798AE W2995AE W3023AE W3221AE W3488AE W3582AE W3984AE | - Optional accessories - MG3710A/MG3740A Operation Manual (Main Unit) MG3710A/MG3740A Operation Manual (IQproducer) MG3710A Operation Manual (Pre-installed Waveform Patterns) MX370073A Operation Manual MX370073B Operation Manual MX370075A Operation Manual MX370084A Operation Manual MX370101A Operation Manual MX370102A Operation Manual MX370103A Operation Manual MX370104A Operation Manual MX370105A Operation Manual MX370106A Operation Manual MX370107A Operation Manual MX370108A Operation Manual MX370110A Operation Manual MX370111A Operation Manual MX370112A Operation Manual MX370113A Operation Manual | Booklet, for MG3710A/MG3740A Main Frame (Operation, Remote Control) Booklet, for IQproducer (Operation for Common Parts) Booklet, for Pre-installed Waveform Patterns (Usage, Detailed Parameters) Booklet, for DFS (for FCC and Japan MIC (TELEC)) Waveform Patterns Booklet, for DFS (for FCC and Japan MIC (TELEC)) Waveform Patterns Booklet, for DFS (ETSI) Waveform Patterns Booklet, for ISDB-Tmm Waveform Patterns Booklet, for HSDPA/HSUPA IQproducer Booklet, for TDMA IQproducer Booklet, for CDMA2000 1xEV-DO IQproducer Booklet, for Multi-carrier IQproducer Booklet, for Mobile WiMAX IQproducer Booklet, for DVB-T/H IQproducer Booklet, for Fading IQproducer Booklet, for LTE IQproducer/LTE-Advanced FDD Option Booklet, for LTE TDD IQproducer/LTE-Advanced TDD Option Booklet, for WLAN IQproducer/802.11ac Option Booklet, for TD-SCDMA IQproducer Booklet, for 5G NR TDD sub-6GHz IQproducer |
| J1539A Z1572A Z1594A MA24105A MA24106A MA24108A MA24118A MA24126A K240B | AUX Conversion Adapter Installation Kit Standard Waveform Pattern for Backup Inline Peak Power Sensor USB Power Sensor Microwave USB Power Sensor Microwave USB Power Sensor Microwave USB Power Sensor Power Divider (K connector) | Converts MG3710A rear-panel AUX connector to BNC connector Required when retrofitting hardware options or installing IQproducer (MX3701xxA) Latest MG3710A Pre-installed waveform pattern set for backup 350 MHz to 4 GHz, Inline type, with USB A to micro-B Cable 50 MHz to 6 GHz, with USB A to mini-B Cable 10 MHz to 8 GHz, with USB A to micro-B Cable 10 MHz to 18 GHz, with USB A to micro-B Cable 10 MHz to 26 GHz, with USB A to micro-B Cable DC to 26.5 GHz, K-J, 50Ω, 1 Wmax |
| MA1612A J0576B J0576D J0127A J0127B J0127C J0322A J0322B J0322C J0322D J0004 J1261B J1261D J0008 B0635A B0657A B0636C B0671A Z0975A Z0541A | Four-Port Junction Pad Coaxial Cord, 1.0 m Coaxial Cord, 2.0 m Coaxial Cord, 1.0 m Coaxial Cord, 2.0 m Coaxial Cord, 0.5 m Coaxial Cord, 0.5 m Coaxial Cord, 1.0 m Coaxial Cord, 1.5 m Coaxial Cord, 2.0 m Coaxial Adapter Ethernet Cable (Shield Type) Ethernet Cable (Shield Type) GPIB Cable, 2.0 m Rack Mount Kit Rack Mount Kit (JIS) Carrying Case Front Cover for 1MW4U Keyboard (USB) USB Mouse | 5 MHz to 3 GHz, N-J N-P · 5D-2W · N-P N-P · 5D-2W · N-P BNC-P · RG-58A/U · BNC-P BNC-P · RG-58A/U · BNC-P BNC-P · RG-58A/U · BNC-P SMA-P · SMA-P, DC to 18 GHz, 50Ω SMA-P · SMA-P, DC to 18 GHz, 50Ω SMA-P · SMA-P, DC to 18 GHz, 50Ω SMA-P · SMA-P, DC to 18 GHz, 50Ω N-P · SMA-J Conversion Adapter, DC to 12.4 GHz Straight-through, 3 m Crossover, 3 m EIA JIS Hard Type. With Casters and B0671A Front Cover |

The following option is installed as standard when ordering the MG3710A. It does not require a separate order.
MX371099A MG3710A Standard Waveform Pattern

Typical (typ.): Performance not warranted. Must products meet typical performance.

Nominal (nom.): Values not warranted. Included to facilitate application of product.

Measured (meas): Performance not warranted. Data actually measured by randomly selected measuring instruments.

Trademarks:

- IQproducer™ is a registered trademark of Anritsu Corporation.
- MATLAB® is a registered trademark of The MathWorks, Inc.
- CDMA2000® is a registered trademark of the Telecommunications Industry Association (TIA-USA).
- The Bluetooth® mark and logos are owned by Bluetooth SIG, Inc. and are used by Anritsu under license.
- Pentium® is registered trademarks of Intel Corporation or its subsidiaries in the USA and other countries.
- Windows® is a registered trademark of Microsoft Corporation in the USA and other countries.
- WiMAX® is a trademark or registered trademark of WiMAX Forum.
- Other companies, product names and service names are registered trademarks of their respective companies.